Invisible RFID Cabinet lock

1: Specifications:

Product Name	Invisible RFID Cabinet lock	Model #	CB-99
Application	Wood Cabinet / Lockers	Unlock Way	RFID Card
Card Chip	M1 Card (13.56MHz)	Working Mode	1-Key Mode and 2-Key Mode
Key Type	Card (by default), Wristband	Working Voltage	DC6V (4pcs AA batteries)
Material	ABS	Battery Life	1 Year
Color	Black	Lock Size	76*76*29.5 mm
Weight	0.25kg / pcs	Installation	≤50 mm Thickness Cabinet

2: Package Include:

Package Details

Lock

Latch

Mifare Card

Wrist bands

IC keytags

Screws

inner box

TEL: +86 755 29450011 (8lines) /   http://www.s4a-access.com /   E-mail: sales@s4a-access.com

Address:6th Floor, Haotai Industrial Zone,Minzhi Road,Longhua New District,Shenzhen,PRC.

3: Operation steps:

1: Package set comes with admin card,take the admin card to swipe once,When hear 1 "beep",within 5 seconds,we need to swipe users cards. Maximum support 13pcs users

2: Instructions:

The initialization button has a small hole near the edge of the battery cover on the back of the lock bolt. Take the toothpick inserts the small hole, we hears 1 "beep" and and then we loose hand immediately. It is called a single tone or a single card. It is called a double tone or double card immediately after pressing 1-2 seconds.

3: The 1st swiping card after factory reset.it will be admin card

4: When low voltage, Swipe user cards, we will hear "beep"   for 8 times, lockers will open, and another 8 beeps,lock tongue will not come out, this indicates that lock is under Normally open status,it reminds users to change battery.

4: Dimension

Dimension for Invisible RFID Cabinet lock

TEL: +86 755 29450011 (8lines) /   http://www.s4a-access.com /   E-mail: sales@s4a-access.com

Address:6th Floor, Haotai Industrial Zone,Minzhi Road,Longhua New District,Shenzhen,PRC.